

# HEXALED 2.0

# CONTRASTE

**Performance 20W / ELV**  
**LumiLEDs COB 1211**  
**PHILIPS XI020C050V042RNP2**

## DIMMING INFORMATIONS

- Dimmers used: ELV
- Audible noise: None
- Number of units tested: 1 to 3

Compagny	Models	Codes	Types	Dimming Performances	
				Programmable	Dimming Range*
LUTRON	SKYLARK	SELV-300P	ELV	NA	8% - 109%
	SKYLARK CONTOUR	CTRP-253P-WH	LED / INC / ELV / MLV	NA	8% - 102%
	DIVA	DVELV-300P	ELV	NA	7% - 107%
	NOVA T	NTELV-600	ELV	NA	15% - 107%
	NOVA T	NTRP-250-WH	ELV	NA	17% - 107%
	MAESTRO	MRF2S-6ELV120-WH	ELV	YES	0% - 113%
	GRAFIK T	GTJ-5NEM-WH	ELV	YES	12% - 99%
	SPACER SYSTEM	SPSELV-600	ELV	NA	17% - 114%
CASÉTA	PD-5NE	LED / INC / ELV / MLV	YES	17% - 116%	
LEVITON	DECORA	DSE06-10Z	ELV	NA	3% - 123%
	DECORA	IPE04-LAW	ELV	SCREW	1% - 108%
	RENOIR II	AWSMT-EAW	ELV	NA	0% - 127%
	RENOIR II	AWSMG-EB	ELV	NA	0% - 127%
	VIZIA +	VPE06-1LZ	ELV	YES	3% - 122%
	Vizia	IPE04-1LZ	ELV	SCREW	8% - 117%
	Decora	6615-P	ELV	SCREW	13% - 115%
Vizia RF +	VRE06-1LZ	ELV	YES	17% - 117%	
COOPER	SKEY AL	SAL06P	ELV	WHEEL	12% - 100%
	ASPIRE RF	RF9540-NDW	ELV	YES	28% - 100%
	DEVINE	DAL06P-C4	ELV	WHEEL	33% - 127%
LEGRAND	ADORNE	ADTP703TUM4 MIN 6W	LED / INC / ELV / MLV	AUTO	22% - 104%
	ADORNE	ADTP700MMTUM2 MIN 50W	LED / INC / ELV / MLV	AUTO	0% - 101%
	ADORNE	ADTH700RMTU MIN 50W	LED / INC / ELV / MLV	AUTO	0% - 98%
	ADORNE	ADWR700MMTU MIN 50W	LED / INC / ELV / MLV	AUTO	0% - 106%
	ADORNE	ADTP700RMTU MIN 50W	LED / INC / ELV / MLV	AUTO	0% - 106%
	ADORNE	ADTH700RMTUW1 MIN 50W	LED / INC / ELV / MLV	AUTO	0% - 106%
	PASS & SEYMOUR	H703PTUW MIN 6W	LED / INC / ELV / MLV	AUTO	1% - 120%
	RADIANT	H703PTUW MIN 6W	LED / INC / ELV / MLV	AUTO	22% - 129%
	RADIANT	LC2101-WH	LED / INC / ELV / MLV	MAN	0% - 106%

\* Full Dimming Range

**NOTE:** The above table shows dimmers that have been tested and have demonstrated proper operation under normal conditions. Each installation being unique, various factors such as load, common neutrals or other electrical products on the circuit can, in certain instances, cause variance in system performance. Read and comply to the dimmer installation instructions. Consult dimming system manufacturer for additional support in operation. Contraste recommends to use dimmers designed to work with LED fixtures. Older dimmers designed for incandescent lamps may cause erratic operation. Do not mix fixtures of different wattages or types on the same dimming circuit. Some dimmers may require more than one fixture for stable operation. The maximum number of fixtures is determined by the dimmer wattage rating with LEDs. Be careful, these dimmers have different ratings depending on the load type. Again, refer to the dimmer installation instructions. For example, if the dimmer rating is 150W with LED, a user may use up to fifteen (15) 10W fixtures. Specifications are subject to change without notice.

Note: Contrast Lighting cannot be held responsible of any compatibility problems between dimmers and Contrast Lighting fixtures.

# CONTRASTE

1009, rue du Parc Industriel  
Lévis (Québec) G6Z 1C5 Canada

Tel.: 1-888-839-4624 Fax: 1-877-839-7057

info@contrastlighting.com  
contrastlighting.com

© 2021 Contrast Lighting M.L. Inc.  
All rights reserved

Contrast Lighting reserves the right to make changes in specifications and/or to discontinue any product at any time without notice or obligation and will not be liable for any consequences resulting from the use of this publication.

# HEXALED 2.0

# CONTRASTE

Performance 28W / ELV  
LumiLEDs COB 1211  
ERP ESS030W-0700-42

## DIMMING INFORMATIONS

- Dimmers used: ELV
- Audible noise: None
- Number of units tested: 1 to 3

Compagny	Models	Codes	Types	Dimming Performances	
				Programmable	Dimming Range*
LUTRON	SKYLARK	SELV-300P	ELV	NA	7% - 100%
	SKYLARK CONTOUR	CTRP-253P-WH	LED / INC / ELV / MLV	NA	7% - 94%
	DIVA	DVELV-300P	ELV	NA	7% - 100%
	NOVA T	NTELV-600	ELV	NA	11% - 100%
	NOVA T	NTRP-250-WH	ELV	NA	12% - 100%
	MAESTRO	MRF2S-6ELV120-WH	ELV	YES	2% - 100%
	GRAFIK T	GTJ-5NEM-WH	ELV	YES	9% - 88%
	SPACER SYSTEM	SPSELV-600	ELV	NA	12% - 100%
LEVITON	CASÉTA	PD-5NE	LED / INC / ELV / MLV	YES	9% - 100%
	DECORA	DSE06-10Z	ELV	NA	5% - 100%
	DECORA	IPE04-LAW	ELV	SCREW	4% - 100%
	RENOIR II	AWSMT-EAW	ELV	NA	0% - 100%
	RENOIR II	AWSMG-EB	ELV	NA	0% - 100%
	VIZIA +	VPE06-1LZ	ELV	YES	2% - 100%
	VIZIA	IPE04-1LZ	ELV	SCREW	7% - 100%
	DECORA	6615-P	ELV	SCREW	12% - 100%
COOPER	VISIA RF +	VRE06-1LZ	ELV	YES	12% - 100%
	SKEY AL	SAL06P	ELV	WHEEL	8% - 100%
	ASPIRE RF	RF9540-NDW	ELV	YES	28% - 100%
LEGRAND	DEVINE	DAL06P-C4	ELV	WHEEL	18% - 100%
	ADORNE	ADTP703TUM4 MIN 6W	LED / INC / ELV / MLV	AUTO	13% - 92%
	ADORNE	ADTP700MMTUM2 MIN 50W	LED / INC / ELV / MLV	AUTO	1% - 94%
	ADORNE	ADTH700RMTU MIN 50W	LED / INC / ELV / MLV	AUTO	1% - 94%
	ADORNE	ADWR700MMTU MIN 50W	LED / INC / ELV / MLV	AUTO	1% - 94%
	ADORNE	ADTP700RMTU MIN 50W	LED / INC / ELV / MLV	AUTO	1% - 94%
	ADORNE	ADTH700RMTUW1 MIN 50W	LED / INC / ELV / MLV	AUTO	2% - 94%
	PASS & SEYMOUR	H703PTUW MIN 6W	LED / INC / ELV / MLV	AUTO	2% - 100%
	RADIANT	H703PTUW MIN 6W	LED / INC / ELV / MLV	AUTO	17% - 100%
	RADIANT	LC2101-WH	LED / INC / ELV / MLV	MAN	1% - 96%

\* Full Dimming Range

**NOTE:** The above table shows dimmers that have been tested and have demonstrated proper operation under normal conditions. Each installation being unique, various factors such as load, common neutrals or other electrical products on the circuit can, in certain instances, cause variance in system performance. Read and comply to the dimmer installation instructions. Consult dimming system manufacturer for additional support in operation. Contraste recommends to use dimmers designed to work with LED fixtures. Older dimmers designed for incandescent lamps may cause erratic operation. Do not mix fixtures of different wattages or types on the same dimming circuit. Some dimmers may require more than one fixture for stable operation. The maximum number of fixtures is determined by the dimmer wattage rating with LEDs. Be careful, these dimmers have different ratings depending on the load type. Again, refer to the dimmer installation instructions. For example, if the dimmer rating is 150W with LED, a user may use up to fifteen (15) 10W fixtures. Specifications are subject to change without notice.

Note: Contrast Lighting cannot be held responsible of any compatibility problems between dimmers and Contrast Lighting fixtures.

# CONTRASTE

1009, rue du Parc Industriel  
Lévis (Québec) G6Z 1C5 Canada

Tel.: 1-888-839-4624 Fax: 1-877-839-7057

info@contrastlighting.com  
contrastlighting.com

© 2021 Contrast Lighting M.L. Inc.  
All rights reserved

Contrast Lighting reserves the right to make changes in specifications and/or to discontinue any product at any time without notice or obligation and will not be liable for any consequences resulting from the use of this publication.

# HEXALED 2.0

# CONTRASTE

Performance 36W / ELV  
LumiLEDs COB 1211  
ERP ESM040W-0900-42

## DIMMING INFORMATIONS

- Dimmers used: ELV
- Audible noise: None
- Number of units tested: 1 to 3

Compagny	Models	Codes	Types	Dimming Performances	
				Programmable	Dimming Range*
LUTRON	CASÉTA	PD-5NE	LED / INC / ELV / MLV	YES	9% - 100%
	DIVA	DVELV-300P	ELV	NA	7% - 100%
	GRAFIK T	GTJ-5NEM-WH	ELV	YES	10% - 93%
	MAESTRO	MRF2S-6ELV120-WH	ELV	YES	2% - 100%
	NOVA T	NTELV-600	ELV	NA	11% - 100%
	NOVA T	NTRP-250-WH	ELV	NA	12% - 100%
	SKYLARK	SELV-300P	ELV	NA	8% - 100%
	SKYLARK CONTOUR	CTRP-253P-WH	LED / INC / ELV / MLV	NA	8% - 98%
	SPACER SYSTEM	SPSELV-600	ELV	NA	11% - 100%
LEVITON	DECORA	DSE06-10Z	ELV	NO	6% - 100%
	DECORA	IPE04-LAW	ELV	SCREW	4% - 100%
	DECORA	6615-P	ELV	SCREW	11% - 100%
	RENOIR II	AWSMT-EAW	ELV	NO	0% - 100%
	RENOIR II	AWSMG-EB	ELV	NO	0% - 100%
	VISIA RF +	VRE06-1LZ	ELV	YES	10% - 100%
	VIZIA	IPE04-1LZ	ELV	SCREW	7% - 100%
VIZIA +	VPE06-1LZ	ELV	YES	2% - 100%	
COOPER	ASPIRE RF	RF9540-NDW	ELV	YES	19% - 100%
	DEVINE	DAL06P-C4	ELV	WHEEL	14% - 100%
	SKEY AL	SAL06P	ELV	WHEEL	15% - 100%
LEGRAND	ADORNE	ADTP703TUM4 MIN 6W	LED / INC / ELV / MLV	AUTO	1% - 97%
	ADORNE	ADTP700MMTUM2 MIN 50W	LED / INC / ELV / MLV	AUTO	1% - 99%
	ADORNE	ADTH700RMTU MIN 50W	LED / INC / ELV / MLV	AUTO	1% - 99%
	ADORNE	ADWR700MMTU MIN 50W	LED / INC / ELV / MLV	AUTO	1% - 97%
	ADORNE	ADTP700RMTU MIN 50W	LED / INC / ELV / MLV	AUTO	2% - 99%
	ADORNE	ADTH700RMTUW1 MIN 50W	LED / INC / ELV / MLV	AUTO	1% - 99%
	PASS & SEYMOUR	H703PTUW MIN 6W	LED / INC / ELV / MLV	AUTO	3% - 100%
	RADIANT	H703PTUW MIN 6W	LED / INC / ELV / MLV	AUTO	17% - 101%
	RADIANT	LC2101-WH	LED / INC / ELV / MLV	AUTO	3% - 100%

\* Full Dimming Range

**NOTE:** The above table shows dimmers that have been tested and have demonstrated proper operation under normal conditions. Each installation being unique, various factors such as load, common neutrals or other electrical products on the circuit can, in certain instances, cause variance in system performance. Read and comply to the dimmer installation instructions. Consult dimming system manufacturer for additional support in operation. Contraste recommends to use dimmers designed to work with LED fixtures. Older dimmers designed for incandescent lamps may cause erratic operation. Do not mix fixtures of different wattages or types on the same dimming circuit. Some dimmers may require more than one fixture for stable operation. The maximum number of fixtures is determined by the dimmer wattage rating with LEDs. Be careful, these dimmers have different ratings depending on the load type. Again, refer to the dimmer installation instructions. For example, if the dimmer rating is 150W with LED, a user may use up to fifteen (15) 10W fixtures. Specifications are subject to change without notice.

Note: Contrast Lighting cannot be held responsible of any compatibility problems between dimmers and Contrast Lighting fixtures.

# CONTRASTE

1009, rue du Parc Industriel  
Lévis (Québec) G6Z 1C5 Canada

Tel.: 1-888-839-4624 Fax: 1-877-839-7057

info@contrastlighting.com  
contrastlighting.com

© 2021 Contrast Lighting M.L. Inc.  
All rights reserved

Contrast Lighting reserves the right to make changes in specifications and/ or to discontinue any product at any time without notice or obligation and will not be liable for any consequences resulting from the use of this publication.

# HEXALED 2.0

# CONTRASTE

Performance 50W / ELV  
LumiLEDs COB 1211  
ERP ESM050W-1200-42

## DIMMING INFORMATIONS

- Dimmers used: ELV
- Audible noise: None
- Number of units tested: 1 to 3

Compagny	Models	Codes	Types	Dimming Performances	
				Programmable	Dimming Range*
LUTRON	SKYLARK	SELV-300P	ELV	NA	8% - 100%
	SKYLARK CONTOUR	CTRP-253P-WH	LED / INC / ELV / MLV	NA	8% - 92%
	DIVA	DVELV-300P	ELV	NA	8% - 97%
	NOVA T	NTELV-600	ELV	NA	11% - 100%
	NOVA T	NTRP-250-WH	ELV	NA	9% - 99%
	MAESTRO	MRF2S-6ELV120-WH	ELV	YES	2% - 100%
	GRAFIK T	GTJ-5NEM-WH	ELV	YES	9% - 89%
	SPACER SYSTEM	SPSELV-600	ELV	NA	12% - 100%
	CASÉTA	PD-5NE	LED / INC / ELV / MLV	YES	10% - 100%
LEVITON	DECORA	DSE06-10Z	ELV	NA	6% - 100%
	DECORA	IPE04-LAW	ELV	SCREW	4% - 99%
	RENOIR II	AWSMT-EAW	ELV	NA	0% - 100%
	RENOIR II	AWSMG-EB	ELV	NA	0% - 100%
	VIZIA +	VPE06-1LZ	ELV	YES	2% - 100%
	VIZIA	IPE04-1LZ	ELV	SCREW	7% - 100%
	DECORA	6615-P	ELV	SCREW	12% - 100%
	VISIA RF +	VRE06-1LZ	ELV	YES	0% - 100%
COOPER	SKEY AL	SAL06P	ELV	WHEEL	9% - 100%
	ASPIRE RF	RF9540-NDW	ELV	YES	15% - 100%
	DEVINE	DAL06P-C4	ELV	WHEEL	19% - 100%
LEGRAND	ADORNE	ADTP703TUM4 MIN 6W	LED / INC / ELV / MLV	AUTO	14% - 92%
	ADORNE	ADTP700MMTUM2 MIN 50W	LED / INC / ELV / MLV	AUTO	4% - 93%
	ADORNE	ADTH700RMTU MIN 50W	LED / INC / ELV / MLV	AUTO	1% - 93%
	ADORNE	ADWR700MMTU MIN 50W	LED / INC / ELV / MLV	AUTO	1% - 94%
	ADORNE	ADTP700RMTU MIN 50W	LED / INC / ELV / MLV	AUTO	1% - 94%
	ADORNE	ADTH700RMTUW1 MIN 50W	LED / INC / ELV / MLV	AUTO	0% - 93%
	PASS & SEYMOUR	H703PTUW MIN 6W	LED / INC / ELV / MLV	AUTO	3% - 100%
	RADIANT	H703PTUW MIN 6W	LED / INC / ELV / MLV	AUTO	3% - 100%
	RADIANT	LC2101-WH	LED / INC / ELV / MLV	MAN	1% - 94%

\* Full Dimming Range

**NOTE:** The above table shows dimmers that have been tested and have demonstrated proper operation under normal conditions. Each installation being unique, various factors such as load, common neutrals or other electrical products on the circuit can, in certain instances, cause variance in system performance. Read and comply to the dimmer installation instructions. Consult dimming system manufacturer for additional support in operation. Contraste recommends to use dimmers designed to work with LED fixtures. Older dimmers designed for incandescent lamps may cause erratic operation. Do not mix fixtures of different wattages or types on the same dimming circuit. Some dimmers may require more than one fixture for stable operation. The maximum number of fixtures is determined by the dimmer wattage rating with LEDs. Be careful, these dimmers have different ratings depending on the load type. Again, refer to the dimmer installation instructions. For example, if the dimmer rating is 150W with LED, a user may use up to fifteen (15) 10W fixtures. Specifications are subject to change without notice.

Note: Contrast Lighting cannot be held responsible of any compatibility problems between dimmers and Contrast Lighting fixtures.

# CONTRASTE

1009, rue du Parc Industriel  
Lévis (Québec) G6Z 1C5 Canada

Tel.: 1-888-839-4624 Fax: 1-877-839-7057

info@contrastlighting.com  
contrastlighting.com

© 2021 Contrast Lighting M.L. Inc.  
All rights reserved

Contrast Lighting reserves the right to make changes in specifications and/or to discontinue any product at any time without notice or obligation and will not be liable for any consequences resulting from the use of this publication.

# HEXALED 2.0

Performance 20W / 0-10V  
LumiLEDs COB 1211  
MAGTECH ESS1025-48-C0500

# CONTRASTE

## DIMMING INFORMATION

- Dimmers used: 0-10V
- Audible noise: None
- Number of units tested: 1 to 3

Compagny	Models	Codes	Types	Dimming Performances	
				Programmable	Dimming Range*
LUTRON	DIVA	DVTV + PP-DV	0-10V	NA	0% - 100%
	DIVA	DVSTV-WH	0-10V	WHEEL	11% - 101%
	NOVA	NFTV-WH + PPDV	0-10V	NA	0% - 100%
	NOVA T	NTSTV-DV	0-10V	NA	12% - 100%
	MAESTRO	MS-Z101-WH	0-10V	YES	12% - 100%
LEVITON	DECORA	DS710-10Z	0-10V	NA	0% - 100%
	ILLUMATECH	IP710-DLZ	0-10V	SCREW	0% - 94%
	RENOIR II	AWSWG-7DW	0-10V	NA	18% - 97%
	LUMINA RF	ZSD07-ADZ	0-10V	YES	0% - 100%
LEGRAND	RADIANT	RH4FBL3PW	0-10V	WHEEL	0% - 100%

\* Full Dimming Range

**NOTE:** The above table shows dimmers that have been tested and have demonstrated proper operation under normal conditions. Each installation being unique, various factors such as load, common neutrals or other electrical products on the circuit can, in certain instances, cause variance in system performance. Read and comply to the dimmer installation instructions. Consult dimming system manufacturer for additional support in operation. Contraste recommends to use dimmers designed to work with LED fixtures. Older dimmers designed for incandescent lamps may cause erratic operation. Do not mix fixtures of different wattages or types on the same dimming circuit. Some dimmers may require more than one fixture for stable operation. The maximum number of fixtures is determined by the dimmer wattage rating with LEDs. Be careful, these dimmers have different ratings depending on the load type. Again, refer to the dimmer installation instructions. For example, if the dimmer rating is 150W with LED, a user may use up to fifteen (15) 10W fixtures. Specifications are subject to change without notice.

Note: Contrast Lighting cannot be held responsible of any compatibility problems between dimmers and Contrast Lighting fixtures.

# CONTRASTE

1009, rue du Parc Industriel  
Lévis (Québec) G6Z 1C5 Canada  
Tel.: 1-888-839-4624 Fax: 1-877-839-7057  
info@contrastlighting.com  
contrastlighting.com

© 2021 Contrast Lighting M.L. Inc.  
All rights reserved

Contrast Lighting reserves the right to make changes in specifications and/or to discontinue any product at any time without notice or obligation and will not be liable for any consequences resulting from the use of this publication.

# HEXALED 2.0

Performance 28W / 0-10V  
LumiLEDs COB 1211  
MAGTECH ESS1025-48-C0700

# CONTRASTE

## DIMMING INFORMATION

- Dimmers used: 0-10V
- Audible noise: None
- Number of units tested: 1 to 3

Compagny	Models	Codes	Types	Dimming Performances	
				Programmable	Dimming Range*
LUTRON	DIVA	DVTV + PP-DV	0-10V	NA	0% - 99%
	DIVA	DVSTV-WH	0-10V	WHEEL	11% - 100%
	NOVA	NFTV-WH + PPDV	0-10V	NA	0% - 100%
	NOVA T	NTSTV-DV	0-10V	NA	12% - 100%
	MAESTRO	MS-Z101-WH	0-10V	YES	12% - 100%
LEVITON	DECORA	DS710-10Z	0-10V	NA	0% - 100%
	ILLUMATECH	IP710-DLZ	0-10V	SCREW	0% - 93%
	RENOIR II	AWSWG-7DW	0-10V	NA	20% - 96%
	LUMINA RF	ZSD07-ADZ	0-10V	YES	0% - 100%
LEGRAND	RADIANT	RH4FBL3PW	0-10V	WHEEL	0% - 100%

\* Full Dimming Range

**NOTE:** The above table shows dimmers that have been tested and have demonstrated proper operation under normal conditions. Each installation being unique, various factors such as load, common neutrals or other electrical products on the circuit can, in certain instances, cause variance in system performance. Read and comply to the dimmer installation instructions. Consult dimming system manufacturer for additional support in operation. Contraste recommends to use dimmers designed to work with LED fixtures. Older dimmers designed for incandescent lamps may cause erratic operation. Do not mix fixtures of different wattages or types on the same dimming circuit. Some dimmers may require more than one fixture for stable operation. The maximum number of fixtures is determined by the dimmer wattage rating with LEDs. Be careful, these dimmers have different ratings depending on the load type. Again, refer to the dimmer installation instructions. For example, if the dimmer rating is 150W with LED, a user may use up to fifteen (15) 10W fixtures. Specifications are subject to change without notice.

Note: Contrast Lighting cannot be held responsible of any compatibility problems between dimmers and Contrast Lighting fixtures.

# CONTRASTE

1009, rue du Parc Industriel  
Lévis (Québec) G6Z 1C5 Canada

Tel.: 1-888-839-4624 Fax: 1-877-839-7057

info@contrastlighting.com  
contrastlighting.com

© 2021 Contrast Lighting M.L. Inc.  
All rights reserved

Contrast Lighting reserves the right to make changes in specifications and/or to discontinue any product at any time without notice or obligation and will not be liable for any consequences resulting from the use of this publication.

# HEXALED 2.0

Performance 36W / 0-10V  
LumiLEDs COB 1211  
MAGTECH ESS1025-48-C0900

# CONTRASTE

## DIMMING INFORMATION

- Dimmers used: 0-10V
- Audible noise: None
- Number of units tested: 1 to 3

Compagny	Models	Codes	Types	Dimming Performances	
				Programmable	Dimming Range*
LUTRON	DIVA	DVTV + PP-DV	0-10V	NA	0% - 100%
	DIVA	DVSTV-WH	0-10V	WHEEL	11% - 100%
	NOVA	NFTV-WH + PPDV	0-10V	NA	0% - 100%
	NOVA T	NTSTV-DV	0-10V	NA	13% - 100%
	MAESTRO	MS-Z101-WH	0-10V	YES	13% - 100%
LEVITON	DECORA	DS710-10Z	0-10V	NA	0% - 100%
	ILLUMATECH	IP710-DLZ	0-10V	SCREW	0% - 94%
	RENOIR II	AWSWG-7DW	0-10V	NA	19% - 91%
	LUMINA RF	ZSD07-ADZ	0-10V	YES	0% - 100%
LEGRAND	RADIANT	RH4FBL3PW	0-10V	WHEEL	0% - 100%

\* Full Dimming Range

**NOTE:** The above table shows dimmers that have been tested and have demonstrated proper operation under normal conditions. Each installation being unique, various factors such as load, common neutrals or other electrical products on the circuit can, in certain instances, cause variance in system performance. Read and comply to the dimmer installation instructions. Consult dimming system manufacturer for additional support in operation. Contraste recommends to use dimmers designed to work with LED fixtures. Older dimmers designed for incandescent lamps may cause erratic operation. Do not mix fixtures of different wattages or types on the same dimming circuit. Some dimmers may require more than one fixture for stable operation. The maximum number of fixtures is determined by the dimmer wattage rating with LEDs. Be careful, these dimmers have different ratings depending on the load type. Again, refer to the dimmer installation instructions. For example, if the dimmer rating is 150W with LED, a user may use up to fifteen (15) 10W fixtures. Specifications are subject to change without notice.

Note: Contrast Lighting cannot be held responsible of any compatibility problems between dimmers and Contrast Lighting fixtures.

# CONTRASTE

1009, rue du Parc Industriel  
Lévis (Québec) G6Z 1C5 Canada

Tel.: 1-888-839-4624 Fax: 1-877-839-7057

info@contrastlighting.com  
contrastlighting.com

© 2021 Contrast Lighting M.L. Inc.  
All rights reserved

Contrast Lighting reserves the right to make changes in specifications and/or to discontinue any product at any time without notice or obligation and will not be liable for any consequences resulting from the use of this publication.

# HEXALED 2.0

# CONTRASTE

**Performance 50W / 0-10V**  
**LumiLEDs COB 1211**  
**PHILIPS XI050C140V054DSM1**

## DIMMING INFORMATIONS

- Dimmers used: 0-10V
- Audible noise: None
- Number of units tested: 1 to 3

Compagny	Models	Codes	Types	Dimming Performances	
				Programmable	Dimming Range*
LUTRON	DIVA	DVTV + PP-DV	0-10V	NA	0% - 100%
	DIVA	DVSTV-WH	0-10V	WHEEL	11% - 100%
	NOVA	NFTV-WH + PPDV	0-10V	NA	0% - 100%
	NOVA T	NTSTV-DV	0-10V	NA	13% - 100%
	MAESTRO	MS-Z101-WH	0-10V	YES	13% - 100%
LEVITON	DECORA	DS710-10Z	0-10V	NA	0% - 100%
	ILLUMATECH	IP710-DLZ	0-10V	SCREW	0% - 94%
	RENOIR II	AWSWG-7DW	0-10V	NA	19% - 91%
	LUMINA RF	ZSD07-ADZ	0-10V	YES	0% - 100%
LEGRAND	RADIANT	RH4FBL3PW	0-10V	WHEEL	0% - 100%

\* Full Dimming Range

**NOTE:** The above table shows dimmers that have been tested and have demonstrated proper operation under normal conditions. Each installation being unique, various factors such as load, common neutrals or other electrical products on the circuit can, in certain instances, cause variance in system performance. Read and comply to the dimmer installation instructions. Consult dimming system manufacturer for additional support in operation. Contraste recommends to use dimmers designed to work with LED fixtures. Older dimmers designed for incandescent lamps may cause erratic operation. Do not mix fixtures of different wattages or types on the same dimming circuit. Some dimmers may require more than one fixture for stable operation. The maximum number of fixtures is determined by the dimmer wattage rating with LEDs. Be careful, these dimmers have different ratings depending on the load type. Again, refer to the dimmer installation instructions. For example, if the dimmer rating is 150W with LED, a user may use up to fifteen (15) 10W fixtures. Specifications are subject to change without notice.

Note: Contrast Lighting cannot be held responsible of any compatibility problems between dimmers and Contrast Lighting fixtures.

# CONTRASTE

1009, rue du Parc Industriel  
 Lévis (Québec) G6Z 1C5 Canada  
 Tel.: 1-888-839-4624 Fax: 1-877-839-7057  
 info@contrastlighting.com  
 contrastlighting.com

© 2021 Contrast Lighting M.L. Inc.  
 All rights reserved

Contrast Lighting reserves the right to make changes in specifications and/or to discontinue any product at any time without notice or obligation and will not be liable for any consequences resulting from the use of this publication.



# HEXALED 2.0

# CONTRASTE

**Performance 20W, 28W and 36W / Addressable****LumiLEDs COB 1211****HI-LUME L3DA4U1UKS-EA050****HI-LUME L3DA4U1UKS-FA070****HI-LUME L3DA4U1UKS-FA090****DIMMING INFORMATIONS**

- Dimmers used: Addressable
- Audible noise: None
- Number of units tested: 1 to 3

Compagny	Models	Codes	Types	Dimming Performances	
				Programmable	Dimming Range*
LUTRON	DIVA	DVF-103P-WH	HI-LUME / ECO-10	WHEEL	1% - 100%
LEVITON	VIZIA + DECORA	VPH06-7LZ (277V seulement)	HI-LUME / ECO-10	YES	1% - 100%
	VIZIA + DECORA	VPH08-1LZ (120V seulement)	HI-LUME / ECO-10	YES	1% - 100%

\* Full Dimming Range

**NOTE:** The above table shows dimmers that have been tested and have demonstrated proper operation under normal conditions. Each installation being unique, various factors such as load, common neutrals or other electrical products on the circuit can, in certain instances, cause variance in system performance. Read and comply to the dimmer installation instructions. Consult dimming system manufacturer for additional support in operation. Contraste recommends to use dimmers designed to work with LED fixtures. Older dimmers designed for incandescent lamps may cause erratic operation. Do not mix fixtures of different wattages or types on the same dimming circuit. Some dimmers may require more than one fixture for stable operation. The maximum number of fixtures is determined by the dimmer wattage rating with LEDs. Be careful, these dimmers have different ratings depending on the load type. Again, refer to the dimmer installation instructions. For example, if the dimmer rating is 150W with LED, a user may use up to fifteen (15) 10W fixtures. Specifications are subject to change without notice.

Note: Contrast Lighting cannot be held responsible of any compatibility problems between dimmers and Contrast Lighting fixtures.

# CONTRASTE

1009, rue du Parc Industriel  
Lévis (Québec) G6Z 1C5 Canada

Tel.: 1-888-839-4624 Fax: 1-877-839-7057

info@contrastlighting.com  
contrastlighting.com© 2021 Contrast Lighting M.L. Inc.  
All rights reserved

Contrast Lighting reserves the right to make changes in specifications and/or to discontinue any product at any time without notice or obligation and will not be liable for any consequences resulting from the use of this publication.

# HEXALED 2.0

# CONTRASTE

**347V / 0-10V only****DIMMING INFORMATION**

- Dimmers used: 0-10V only
- Audible noise: None
- Number of units tested: 1 to 3

Compagny	Models	Codes	Types	Dimming Performances	
				Programmable	Dimming Range*
LUTRON	DIVA	DVTV + PP347H	0-10V	NO	2% - 100%
LUTRON	NOVA	NFTV-WH + PP347H	0-10V	NO	2% - 100%

\* Full Dimming Range

**NOTE:** The above table shows dimmers that have been tested and have demonstrated proper operation under normal conditions. Each installation being unique, various factors such as load, common neutrals or other electrical products on the circuit can, in certain instances, cause variance in system performance. Read and comply to the dimmer installation instructions. Consult dimming system manufacturer for additional support in operation. Contraste recommends to use dimmers designed to work with LED fixtures. Older dimmers designed for incandescent lamps may cause erratic operation. Do not mix fixtures of different wattages or types on the same dimming circuit. Some dimmers may require more than one fixture for stable operation. The maximum number of fixtures is determined by the dimmer wattage rating with LEDs. Be careful, these dimmers have different ratings depending on the load type. Again, refer to the dimmer installation instructions. For example, if the dimmer rating is 150W with LED, a user may use up to fifteen (15) 10W fixtures. Specifications are subject to change without notice.

Note: Contrast Lighting cannot be held responsible of any compatibility problems between dimmers and Contrast Lighting fixtures.

# CONTRASTE

1009, rue du Parc Industriel  
Lévis (Québec) G6Z 1C5 Canada

Tel.: 1-888-839-4624 Fax: 1-877-839-7057

info@contrastlighting.com  
contrastlighting.com

© 2021 Contrast Lighting M.L. Inc.  
All rights reserved

Contrast Lighting reserves the right to make changes in specifications and/or to discontinue any product at any time without notice or obligation and will not be liable for any consequences resulting from the use of this publication.