

**ARKOS – SPIN**

ELV - 120V

**CONTRASTE****DIMMING INFORMATION**

- Dimmers used: ELV only
- Audible noise: None
- Number of units tested: 1 to 10

Company	Models	Codes	Types	Minimum luminaire (per circuit)	Dimming Performances		
					Programmable	* Dimming Range	** Optimal Performance
LUTRON  DISCONTINUED  DISCONTINUED  DISCONTINUED	SKYLARK	SELV-300P	ELV	1	NA	7% - 100%	7% - 100%
	DIVA	DVELV-300P	ELV	1	NA	7% - 100%	7% - 100%
	NOVA T	NTELV-600	ELV	1	NA	9% - 100%	9% - 100%
	RADIO RA2	RRD-6NA-WH	ELV	1	YES	2% - 100%	2% - 100%
	Maestro	MAELV-600 Slider	ELV	1	NA	12% - 100%	12% - 100%
	Maestro	MAELV-600 Pull Tab	ELV	1	YES	2% - 100%	2% - 100%
	Maestro	MRF2-6ELV-120	ELV	1	YES	2% - 100%	2% - 100%
DISCONTINUED	Grafik T	GTJ-5NEM-WH	ELV	1	YES	9% - 100%	9% - 100%
	Spacer System	SPSELV-600	ELV	1	NA	11% - 100%	11% - 100%
LEVITON	DECORA	DSE06-10Z	ELV	1	NA	5% - 100%	9% - 100%
	DECORA	IPE04-LAW	ELV	1	YES	4% - 100%	9% - 100%
	RENOIR II	AWSMT-EAW	ELV	1	NA	0% - 100%	16% - 100%
	RENOIR II	AWSMG-EB	ELV	1	NA	0% - 100%	16% - 100%
	VIZIA +	VPE06-1LZ	ELV	1	YES	4% - 100%	4% - 100%
	Vizia	IPE04-1LZ	ELV	1	YES	5% - 100%	5% - 100%
	Decora	6615-P	ELV	1	YES	11% - 100%	11% - 100%
COOPER	ASPIRE RF	RF9540-NDW	ELV	1	YES	15% - 100%	15% - 100%
	DEVINE	DAL06P-C4	ELV	1	YES	8% - 100%	14% - 100%

\* Full Dimming Range

\*\* Optimal Performance: Dimming range for ideal synchronized startup conditions

The use of incandescent dimmers with LED is not recommended by dimmer manufacturers.

For any compatibility problems, consult the dimmer manufacturer.

Note: Contrast Lighting cannot be held responsible of any compatibility problems between dimmers and Contrast Lighting fixtures.

**CONTRASTE**